

## Avaya - SIP Integration with Zoom

Please make sure the Login Name is the Extension

Identity \*

* Last Name:	<input type="text" value="Zoom US"/>
* First Name:	<input type="text" value="wof"/>
Middle Name:	<input type="text"/>
Description:	<input type="text"/>
Update Time:	February 10, 2017 11:2
* Login Name:	<input type="text" value=""/> <small>Enter extension URL, if [4325@company.com]</small>
* Authentication Type:	Basic <input type="text"/>
<a href="#">Change Password</a>	
Source:	<input type="text" value="local"/>
Localized Display Name:	<input type="text" value="Zoom US, wof"/>
Endpoint Display Name:	<input type="text" value="Zoom US, wof"/>
Title:	<input type="text"/>
Language Preference:	English (United States) <input type="text"/>
Time Zone:	<input type="text"/>
Employee ID:	<input type="text"/>
Department:	<input type="text"/>
Company:	<input type="text"/>

Address \*

Under Communication Profile add the Handle and Domain:

Handle: Enter extension for Handle

Domain: Enter company Domain

Session Manager Profile:

Select appropriate SM for Primary and Secondary usage

The screenshot shows a web interface with several sections:

- Communication Profile:** Includes a password field, buttons for New, Delete, Done, and Cancel, and a table with one row: Primary.
- Communication Address:** Includes buttons for New, Edit, and Delete, and a table with one row: Always SIP.
- Session Manager Profile:** Includes fields for Primary Session Manager, Secondary Session Manager, Survivability Server, and Max. Simultaneous Devices.

**Communication Profile Table:**

Name
Primary

**Communication Address Table:**

Type	Handle	Domain
Always SIP	Enter extension for Handle	Enter company Domain

**Session Manager Profile Table:**

Primary	Secondary	Maxdman
209	0	209

  

Primary	Secondary	Maxdman
0	209	209

Under Call Routing Settings make the Home Location based on correct routing preference.

The image shows a configuration interface with two main sections: "Application Sequences" and "CM Endpoint Profile".

**Application Sequences:**

- Origination Sequence: SAT6PROCR-SEQ
- Termination Sequence: SAT6PROCR-SEQ
- Call Routing Settings: Select correct routing preference.
- Home Location: [Redacted]
- Conference Factory Set: (None)

**CM Endpoint Profile:**

- System: SAT6PROCR
- Profile Type: Endpoint
- Use existing endpoints:
- Extension: [Redacted] [Endpoint Editor](#)
- Template: 9603\_SIP
- Set Type: vccoSIP
- Security Code: [Redacted]
- Port: 502503
- Voice Mail Number: [Redacted]
- Preferred Handle: (None)
- Enhanced Call-Info display for 1-line phones:
- Delete Endpoint on Unassign of Endpoint from User or on Delete User:
- Override Endpoint Name: